

### VISTA-50P



*With its powerful performance and reliability, the VISTA-50P is the solution for all your installation needs.*

The VISTA-50P is a superior control panel that provides flexibility of up to eight independent partitions with the economy of a single control.

#### Dependable features to meet your most demanding installations:

- ◆ Nine hardwired zones standard
- ◆ Eight partitions standard
- ◆ 75 user codes work in all partitions
- ◆ Seven authority levels
- ◆ 5800 wireless compatibility
- ◆ Supports two-wire multiplex
- ◆ 87 total zones
- ◆ 224 event memory log/printer option
- ◆ Scheduling of events (real time clock)
- ◆ Keypad macro features
- ◆ Master console option for viewing all partitions at a glance
- ◆ Common lobby logic
- ◆ Fast downloading
- ◆ Supports up to 16 relays and/or X-10
- ◆ Quick start programming
- ◆ False alarm features

#### End users will appreciate the easy to use convenience and control features of the Vista-50P:

- ◆ Wireless remote control - single button system operation:
  - 5804 - a four button programmable wireless key
  - 5804BD - a bi-directional button programmable wireless key with system status feedback
- ◆ Single or dual button wireless personal panic:
  - 5802MN - 5802MN2
- ◆ Home control features that activate lights, appliances, garage doors, and numerous other devices
- ◆ Vista Interactive Phone Module (VIP) that gives the end user control of their system from any touch tone phone. The 4285 VIP responds in English, with a vocabulary of over 100 words
- ◆ Full English display keypads for clear understanding of system status and zone locations
- ◆ Time event applications:
  - Open garage doors and turn on the lights
  - Provides that "lived in look" while away from home
  - Ability to limit access to parts of the home at certain times

## VISTA-50P

### SPECIFICATIONS:

#### ELECTRICAL:

- ◆ Aux power 12 VDC, 750mA max
- ◆ 16.5 VAC/40 VA transformer
- ◆ Alarm output 12 VDC, 2.8 Amps max
- ◆ For UL installations, combined Aux and alarm output cannot exceed 750mA

#### OUTPUT CONTROL:

- ◆ Supports up to four relay boards (part no. 4204)
- ◆ Supports four relays for a total of 16
- ◆ Optional X-10 transformer/interface (part no. 4300) maybe used to control X-10 receiving devices
- ◆ Each X-10 receiver address counts as one relay when computing total relays
- ◆ Real time clock can be used for relay/X-10 control

#### ZONES:

- ◆ Eight hardwired zones
  - Selectable response: 10msec, 350msec, 750msec
  - Assignable to any partition
  - 16 zone types to choose from
  - Programmable swinger suppression

### SUPPORTED DEVICES

#### Hardwired Expansion Devices:

- ◆ 4208 eight zone expansion module
- ◆ Powerline support - 4300 transformer/interface
- ◆ Keypads
  - 6139 custom English (required for programming) -100mA
  - 6128 fixed English LCD-85mA/40mA
- ◆ Voice module 4285 VIP-160mA
- ◆ Two wire smoke detectors
- ◆ Duct detectors
- ◆ Polling loop devices
- ◆ Key Switch devices

### WIRELESS RECEIVER SYSTEMS:

- ◆ 5800 Series
  - 5881L up to 8 zones-50mA
  - 5881M up to 16 zones-50mA
  - 5881H up to 86 zones-50mA
- ◆ All Receivers Support
  - Diversity reception with two antennae
  - Remote mounting for best location
  - Use of second receiver for maximum coverage or tough installations
  - Unique supervision and low battery indications by point

### TRANSMITTERS:

- ◆ 5800 Series
  - Three volt Duracell lithium batteries
  - One mile range
  - Tamper standard

### AGENCY LISTINGS:

- ◆ UL Residential Fire and Burglary and CFM

### COMMUNICATIONS:

- ◆ Touch tone or pulse
- ◆ Formats supported: ADEMCO Contact ID, ADEMCO 4 + 2 Express, ADEMCO low speed
- ◆ 3+1, 4+1 and 4+2 reporting
- ◆ Reporting capabilities: Split, Dual, Split/Dual
- ◆ Low battery reports 11.2-11.6 VDC
- ◆ Expanded reporting
- ◆ Up to four digit PABX code supported
- ◆ True dial tone detection
- ◆ Double pole line seizure
- ◆ AC loss and restoral reporting supported

#### Ordering Information:

Part No.	Description
VISTA-50P	Control Panel